

AdaptaSwitch™ 600XC

2Gx

CUSTOMER SUPPORT INFORMATION Order toll-free in the U.S.: Call 877-877-BBOX (outside U.S. call 724-746-5500)
FREE technical support 24 hours a day, 7 days a week; Call 724-746-5500 or fax 724-746-0746
Mailing address: **Black Box Corporation**, 1000 Park Drive, Lawrence, PA 15055-1018
Web site: www.blackbox.com
E-mail: info@blackbox.com

LED Indicators:

Function	Color	Description
Link/Act	Green	Off-No Linkdetected. On - Link detected. Flashing-Data Received.

Supported Distances:

Cable Type	Distances
Multimode 850nm:	220 m-550 m
Single-mode 1300nm:	5 km/3.1 mi.
Single-mode, LH 1300nm:	20 km/12.5 mi.
Single-mode, LH 1550nm:	50 km/31 mi.

Dimensions / Weight: W:6.5"xD:8.0"xH:1.75" / 1.5lb.
Power: 110/230VAC, 50/60Hz, 300mA
Operating Temp: 0 to 40 degrees C
Storage Temp: -40 to 75 degrees C
Humidity: 0-90% (non-condensing)

Overview and Description:

The AdaptaSwitch™ 600XC described here is a two port 1000Base fiber switch. It supports Multimode (MM) and Single-mode (SM) fiber.

Model	Fiber	Distance
LB6610A	2@SC,MM,850nm	550 m
LB6612A	1@SC,MM,Sx,850nm 1@SC,SM,Lx,1300nm	550 m 3.1 mi.
LB6613A	1@SC,MM,Sx,850nm 1@SC,SM,Lx,LH,1300nm	550 m 12.5 mi.
LB6614A	1@SC,MM,Sx,850nm 1@SC,SM,LLx,LH,1550nm	550 m 31 mi.
LB6610A-LX	2@SM 1300nm,SC,1300nm	3.1 mi.
LB6623A	1@SC,SM,Lx,1300nm 1@SC,SM,Lx,LH,1300nm	3.1 mi. 12.5 mi.
LB6624A	1@SC,SM,Lx,1300nm 1@SC,SM,LLx,LH,1550nm	3.1 mi. 31 mi.
LB6610A-L	2@SM,LH,SC,1300nm	12.5 mi.
LB6610A-LLH	2@SM,LH,SC,1550nm	31 mi.

Installation and Configuration:

Power Adapter Notice:

1. This Model uses internal power supplies that are capable of auto switching from 100-230V, and are supplied with a U.S. type NEMA 5-15 power cable.
2. For products being shipped outside of the U.S., the user is required to install a properly grounded IEC 320-appliance cable with a minimum rating of 10 AMPs.

TRADEMARKS

All applied-for and registered trademarks are the property of their respective owners.

FEDERAL COMMUNICATIONS COMMISSION AND CANADIAN DEPARTMENT OF COMMUNICATIONS RADIO FREQUENCY INTERFERENCE STATEMENTS

This equipment generates, uses, and can radiate radio frequency energy and if not installed and used properly, that is, in strict accordance with the manufacturer's instructions, may cause interference to radio communication. It has been tested and found to comply with the limits for a Class A computing device in accordance with the specifications in subpart J of Part 15 of FCC rules, which are designed to provide reasonable protection against such interference when the equipment is operated in a residential area is likely to be cause interference, in which case the user at his own expense will be required to take whatever measures may be necessary to correct the interference.

Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

This digital apparatus does not exceed the Class A limits for radio noise emission from digital apparatus set out in the Radio Interference Regulation of the Canadian Department of Communications.

Le présent appareil numérique n'émet pas de bruits radioélectriques dépassant les limites applicables aux appareils numériques de la classe A prescrites dans le Règlement sur le brouillage radioélectrique publié par le ministère des Communications du Canada.

3. User-supplied cables must meet the required safety agency approvals, applicable international standards and electrical ratings for the region.

WARNING!

Before inserting the Power cord, verify that the power on the unit is appropriate for your AC line voltage source.

Mounting and Cable Attachment:

The AdaptaSwitch 600XC is designed to be used as a tabletop unit.

After connecting to an appropriate power outlet, attach the AdaptaSwitch 600XC via appropriate SC fiber cables to Gigabit Fast Ethernet fiber switches, hubs or workstations. The fiber's transmit (Tx) must attach to the receive side on the opposing device and the receive (Rx) must attach to the transmit side.

Notes:

©Copyright 1999-2003. Black Box Corporation. All rights reserved.

1000 Park Drive • Lawrence, PA 15055-1018
724-746-5500 • Fax 724-746-0746

12. Precación debe ser tomada de tal manera que la tierra física y la polarización del equipo no sea eliminada.
13. Los cables de la fuente de poder deben ser guiados de tal manera que no sean pisados ni pellizcados por objetos colocados sobre o contra ellos, poniendo particular atención a los contactos y receptáculos donde salen del aparato.
14. El equipo eléctrico debe ser limpiado únicamente de acuerdo a las recomendaciones del fabricante.
15. En caso de existir, una antena externa deberá ser localizada lejos de las líneas de energía.
16. El cable de corriente deberá ser desconectado del cuando el equipo no sea usado por un largo periodo de tiempo.
17. Cuidado debe ser tomado de tal manera que objetos líquidos no sean derramados sobre la cubierta u orificios de ventilación.
18. Servicio por personal calificado deberá ser provisto cuando:
 - A: El cable de poder o el contacto ha sido dañado; u
 - B: Objetos han caído o líquido ha sido derramado dentro del aparato; o
 - C: El aparato ha sido expuesto a la lluvia; o
 - D: El aparato parece no operar normalmente o muestra un cambio en su desempeño; o
 - E: El aparato ha sido tirado o su cubierta ha sido dañada.

LED Indicators:

Function	Color	Description
Link/Act	Green	Off-No Linkdetected. On - Link detected. Flashing-Data Received.

Supported Distances:

Cable Type	Distances
Multimode 850nm:	220 m-550 m
Single-mode 1300nm:	5 km/3.1 mi.
Single-mode, LH 1300nm:	20 km/12.5 mi.
Single-mode, LH 1550nm:	50 km/31 mi.

Dimensions / Weight: W:6.5"xD:8.0"xH:1.75" / 1.5lb.

Power: 110/230VAC, 50/60Hz, 300mA

Operating Temp: 0 to 40 degrees C

Storage Temp: -40 to 75 degrees C

Humidity: 0-90% (non-condensing)

TRADEMARKS

All applied-for and registered trademarks are the property of their respective owners.

FEDERAL COMMUNICATIONS COMMISSION AND CANADIAN DEPARTMENT OF COMMUNICATIONS RADIO FREQUENCY INTERFERENCE STATEMENTS

This equipment generates, uses, and can radiate radio frequency energy and if not installed and used properly, that is, in strict accordance with the manufacturer's instructions, may cause interference to radio communication. It has been tested and found to comply with the limits for a Class A computing device in accordance with the specifications in subpart J of Part 15 of FCC rules, which are designed to provide reasonable protection against such interference when the equipment is operated in a commercial environment. Operation of this equipment in a residential area is likely to be cause interference, in which case the user at his own expense will be required to take whatever measures may be necessary to correct the interference.

Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

This digital apparatus does not exceed the Class A limits for radio noise emission from digital apparatus set out in the Radio Interference Regulation of the Canadian Department of Communications.

Le présent appareil numérique n'émet pas de bruits radioélectriques dépassant les limites applicables aux appareils numériques de la classe A prescrites dans le Règlement sur le brouillage radioélectrique publié par le ministère des Communications du Canada.

NORMAS OFICIALES MEXICANAS (NOM)

ELECTRICAL SAFETY STATEMENT

1. Todas las instrucciones de seguridad y operación deberán ser leídas antes de que el aparato eléctrico sea operado.
2. Las instrucciones de seguridad y operación deberán ser guardadas para referencia futura.
3. Todas las advertencias en el aparato eléctrico y en sus instrucciones de operación deben ser respetadas.
4. Todas las instrucciones de operación y uso deben ser seguidas.
5. El aparato eléctrico no deberá ser usado cerca del agua—por ejemplo, cerca de la tina de baño, lavabo, sótano mojado o cerca de una alberca, etc.
6. El aparato eléctrico debe ser usado únicamente con carritos o pedelstales que sean recomendados por el fabricante.
7. El aparato eléctrico debe ser montado a la pared o al techo sólo como sea recomendado por el fabricante.
8. Servicio—El usuario no debe intentar dar servicio al equipo eléctrico más allá a lo descrito en las instrucciones de operación. Todo otro servicio deberá ser referido a personal de servicio calificado.
9. El aparato eléctrico debe ser situado de tal manera que su posición no interfiera su uso. La colocación del aparato eléctrico sobre una cama, sofá, alfombra o superficie similar puede bloquea la ventilación, no se debe colocar en libreros o gabinetes que impidan el flujo de aire por los orificios de ventilación.
10. El equipo eléctrico deber ser situado fuera del alcance de fuentes de calor como radiadores, registros de calor, estufas u otros aparatos (incluyendo amplificadores) que producen calor.
11. El aparato eléctrico deberá ser conectado a una fuente de poder sólo del tipo descrito en el instructivo de operación, o como se indique en el aparato.

12. Precación debe ser tomada de tal manera que la tierra física y la polarización del equipo no sea eliminada.
13. Los cables de la fuente de poder deben ser guiados de tal manera que no sean pisados ni pellizcados por objetos colocados sobre o contra ellos, poniendo particular atención a los contactos y receptáculos donde salen del aparato.
14. El equipo eléctrico debe ser limpiado únicamente de acuerdo a las recomendaciones del fabricante.
15. En caso de existir, una antena externa deberá ser localizada lejos de las líneas de energía.
16. El cable de corriente deberá ser desconectado del cuando el equipo no sea usado por un largo periodo de tiempo.
17. Cuidado debe ser tomado de tal manera que objetos líquidos no sean derramados sobre la cubierta u orificios de ventilación.
18. Servicio por personal calificado deberá ser provisto cuando:
 - A: El cable de poder o el contacto ha sido dañado; u
 - B: Objetos han caído o líquido ha sido derramado dentro del aparato; o
 - C: El aparato ha sido expuesto a la lluvia; o
 - D: El aparato parece no operar normalmente o muestra un cambio en su desempeño; o
 - E: El aparto ha sido tirado o su cubierta ha sido dañada.



AdaptaSwitch™ 600XC
2Gx

Overview and Description:

The AdaptaSwitch™ 600XC described here is a two port 1000Base fiber switch. It supports Multimode (MM) and Single-mode (SM) fiber.

Model	Fiber	Distance
LB6610A	2@SC,MM,850nm	550 m
LB6612A	1@SC,MM,Sx,850nm	550 m
	1@SC,SM,Lx,1300nm	3.1 mi.
LB6613A	1@SC,MM,Sx,850nm	550 m
	1@SC,SM,Lx,LH,1300nm	12.5 mi.
LB6614A	1@SC,MM,Sx,850nm	550 m
	1@SC,SM,LLx,LH,1550nm	31 mi.
LB6610A-LX	2@SM 1300nm,SC,1300nm	3.1 mi.
LB6623A	1@SC,SM,Lx,1300nm	3.1 mi.
	1@SC,SM,Lx,LH,1300nm	12.5 mi.
LB6624A	1@SC,SM,Lx,1300nm	3.1 mi.
	1@SC,SM,LLx,LH,1550nm	31 mi.
LB6610A-L	2@SM,LH,SC,1300nm	12.5 mi.
LB6610A-LLH	2@SM,LH,SC,1550nm	31 mi.

Installation and Configuration:

Power Adapter Notice:

1. This Model uses internal power supplies that are capable of auto switching from 100-230V, and are supplied with a U.S. type NEMA 5-15 power cable.
2. For products being shipped outside of the U.S., the user is required to install a properly grounded IEC 320-appliance cable with a minimum rating of 10 AMPs.

3. User-supplied cables must meet the required safety agency approvals, applicable international standards and electrical ratings for the region.

WARNING!
Before inserting the Power cord, verify that the power on the unit is appropriate for your AC line voltage source.

Mounting and Cable Attachment:

The AdaptaSwitch 600XC is designed to be used as a tabletop unit.

After connecting to an appropriate power outlet, attach the AdaptaSwitch 600XC via appropriate SC fiber cables to Gigabit Fast Ethernet fiber switches, hubs or workstations. The fiber's transmit (Tx) must attach to the receive side on the opposing device and the receive (Rx) must attach to the transmit side.

Notes:

CUSTOMER SUPPORT INFORMATION Order toll-free in the U.S.: Call 877-877-BBOX (outside U.S. call 724-746-5500)
FREE technical support 24 hours a day, 7 days a week; Call 724-746-5500 or fax 724-746-0746
Mailing address: **Black Box Corporation**, 1000 Park Drive, Lawrence, PA 15055-1018
Web site: www.blackbox.com
E-mail: info@blackbox.com